



Simmons SD600 Firmware Release Notes

To update your SD600 module:

Note: This will reset any settings and user kits you have in the module

1. Connect a USB cable from your computer to the module.
2. Open *Simmons Flash Upload* for Mac or Windows, available from the [Simmons website](#).
3. The software should alert you that the module is connected and will report the current firmware version.
4. Click the Browse button in the application, select the ROM file that you downloaded. The update file needs to be Un-Zipped and should end with “.bin”
5. Click Update.
6. When the update is complete, disconnect the power to the module and then plug it back in.
7. Hold + and – while powering on to reset the module.

Changes in Firmware Version 20190621:

- An assignable MIDI note number has been added for the half-open hi hat
- Assignable MIDI note numbers are saved when power is switched off.