



Simmons Wav Transfer Program Instructions

This software program will transfer standard WAV files to your **Simmons SD1200** or **SD2000** module through USB.

Steps to load in the WAV files:

1. Connect the module to your computer with a standard USB cable to the "USB to Host" jack.
2. Turn on the module. It sometimes takes a few seconds for the computer to see the connection.
3. Start the Simmons WAV Transfer program. The program should show "Connected to Simmons Module."
4. Click on the "Select Wav" button in the program to select .wav files to transfer. The program accepts 22kHz to 48kHz files, 16-bit or 24-bit.
5. Click on the "Upload" button in the program to send the files to the module.
6. Once the .wav files are transferred you will need to restart your module by unplugging the module from the AC adapter input.
7. Re-plug in the module and restart the module. You will then need to assign the .wav files to the User wav. programs. Refer to your SD1200 manual (page 21) or SD2000 manual (page 24) for instructions.

Other functions:

Clear All: Clears the list of .wav files

Delete: Deletes a .wav file from the upload list.

Help: Opens the Read Me file.

Save List: Saves the list of files that you have selected to upload.

Load List: Loads the list that you have saved.

Note: If you already have samples in the module, sending samples again will overwrite those files.